


Order number: 20510053

Open text field 1:



- For switching between input signals from two satellites (multi-feed system) or two subscriber outlets from different multi-switches in multi-feed systems with three or four satellites
- Multi-feed reception from three or four satellites is possible by cascading
- Control signals (14/18 V, 0/22 kHz) and DiSEqC™ are connected through to the selected input. The second input is voltage-free
- For indoor installation
- Two inputs / one output
- Configuration (rotary switch) allows switching between a choice of DiSEqCTM commands for position A/B, option A/B or uncommitted switch 1
- Reception of terrestrial range only possible with receiver switched on



Hersteller: Kathrein

EXR 121

Product information "EXR 121"

DiSEqC switching matrix 2 to 1 - F connectors - Power supply: 28 mA from satellite receiver - DiSEqC controller: Position A/B, option A/B or uncommitted switch

Type:	EXR 121
Order no.:	20510053
Subscriber connections:	1
Inputs:	2 x terr./Sat-ZF (A/B)
Through loss:	2 dB
Decoupling inputs:	25 dB
Control using DiSEqC™:	Configurable for DiSEqC™ commands
Current drain per subscriber:	Typ. 28 mA
Max. allowed remote feed current per user connected:	350 mA
Typical voltage drop (at 350-mA load):	0.4 V
Frequency range:	47-2150 MHz
Switch position 1:	Position A/B
Switch position 2:	Option A/B
Switch position 3:	"Uncommitted switch" On Off
Nominal impedance:	75 Ω
Output isolation:	- dB
Connections:	F connectors
Ambient temperature range:	-20 to +55 °C
Dimensions (W x H x D):	35 x 74 x 21 mm
Packaging unit/weight:	1 (10)/0.4 pc/kg

Mehr Bilder zu "EXR 121"

