


Order number: 20510054

Open text field 1:

- For switching between input signals from two satellites (multi-feed system) or two subscriber outlets from different multi-switches in multi-feed systems with three or four satellites
- Configuration (rotary switch) allows switching between DiSEqC™ commands for position A/B, option A/B or uncommitted switch 1
- Multi-feed reception from three or four satellites is possible by cascading
- Control signals (14/18 V, 0/22 kHz) and DiSEqC™ are connected through to the selected input. The second input is voltage-free
- For indoor installation
- 4 x 2 sat IF inputs/one output (corresponding to 4 x EXR 121, e.g. for multi-feed reception with 2 x UAS 585)
- Reception of terrestrial range also possible when receiver is switched off



Hersteller: Kathrein

## EXR 124

### Product information "EXR 124"

DiSEqC switching matrix 4 x 2 to 1 - F connectors - Power supply: 31 mA from satellite receiver - DiSEqC controller:

Position A/B or option A/B

Type:	EXR 124
Order no.:	20510054
Subscriber connections:	4 x 1
Inputs:	1 x terrestrial (terr.) 4 x 2 x Sat IF (1A 2A 3A 4A / 1B 2B 3B 4B)
Through loss:	9/2 dB
Decoupling inputs:	-30 dB
Control using DiSEqC™:	Configurable for DiSEqC™ commands
Current drain per subscriber:	Typ. 31 mA
Max. allowed remote feed current per user connected:	350 mA
Typical voltage drop (at 350-mA load):	0.28 V
Frequency range:	5-862 950-2150 MHz
Switch position 1:	Position A/B
Switch position 2:	Option A/B
Switch position 3:	"Uncommitted switch" On Off
Nominal impedance:	75 Ω.
Output isolation:	25/40 dB
Connections:	F connectors
Permissible ambient temperature:	-20 to +55 °C
Dimensions (W x H x D):	112 x 148 x 42 mm
Packaging unit/weight:	1 (10)/0.5 pc/kg

### Mehr Bilder zu "EXR 124"

